

Small Format Mixers

XENYX 302USB

Premium 5-Input Mixer with XENYX Mic Preamp and USB/Audio Interface

- Ultra-compact and ultra-low noise analog mixer with USB/Audio interface
- Powered through USB or external adaptor
- Built-in stereo USB/Audio interface to connect directly to your computer
- Free audio recording, editing and podcasting software plus 150 instrument/effect plug-ins and ultra-low latency driver downloadable
- State-of-the-art XENYX Mic Preamp comparable to stand-alone boutique preamps
- Neo-classic "British" 2-band graphic EQ for warm and musical sound
- 2-Track input assignable to Headphone or Main Mix output
- Main Mix plus separate Phones output
- High-quality components and exceptionally rugged construction ensure long life
- Conceived and designed by BEHRINGER Germany



Need a handy little mixer you can grab with your laptop on the way out the door? Or maybe you don't want to give up valuable desktop real estate to a large mixer? The new XENYX 302USB is ideally suited for a small home studio or the on-the-go recording enthusiast. At approximately 4" long and 5" wide (117 x 135 mm), the XENYX 302USB respects your desk space, while providing a phantom-powered XLR & 1/4" combination socket, stereo USB/Line channel plus a dedicated 2-Track input.

Small, but mighty!

Don't let the XENYX 302USB's diminutive size fool you—this little gem is loaded with features typically reserved for larger, more expensive mixers. For instance, we equipped the Mic input with our XENYX mic preamp,


which is legendary for its sonic clarity and high-headroom performance, and we included phantom power for use with high-quality condenser mics. We also gave the Mic and Line/USB channels our 2-band British-style EQs (Low and High), and provide a 2-Track input that can be assigned to either the Main Mix or Phones.

You can even power the XENYX 302USB from your computer's USB port, which is great for capturing the sounds of migratory birds in flight, or for posting your podcast straight to the Web. Sports announcers, radio and TV reporters will definitely want one of these in their field bag. Incredible sonic performance, versatility and extreme value in a small package—that's the XENYX 302USB!




XENYX 302USB


Front Panel



XENYX 302USB recording setup



XENYX 302USB podcasting setup



XENYX 302USB

Specifications

Mic Input

Microphone Input

Type	XLR/¼" combo connector, electronically balanced
------	---

Mic E.I.N. (20 Hz - 20 kHz)

@ 0 Ω source resistance	-130 dB / -133.1 dB A-weighted
@ 50 Ω source resistance	-128 dB / -131.5 dB A-weighted
@ 150 Ω source resistance	-127 dB / -129.8 dB A-weighted
Frequency response (-1 dB)	18 Hz - 40 kHz
Frequency response (-3 dB)	< 10 Hz - 75 kHz
Gain range	+15 dB to +55 dB
Max. input level	+12 dBu @ +10 dB Gain
Impedance	2 kΩ
Signal-to-noise ratio	98 dB / 101 dB A-weighted (0 dBu in @ +22 dB Gain)
Distortion (THD+N)	0.013%

Frequency Response (Mic In → Main Out)

18 Hz - 40 kHz	+0 dB / -1 dB
10 Hz - 75 kHz	+0 dB / -3 dB

Stereo Line Input

Type	RCA jacks, unbalanced
Impedance	6 kΩ
Gain range	-∞ to +20 dB
Max. input level	+20 dBu

2-Track In

Type	RCA jacks, unbalanced
Impedance	20 kΩ
Max. input level	+20 dBu

Headset Mic In

Type	¼" TRS mini jack
Impedance	6 kΩ
Max. input level	+22 dBu @ Gain Min

Equalizer

Low	80 Hz / ±15 dB
High	12 kHz / ±15 dB

Main Outputs

Type	RCA, unbalanced
Impedance	470 Ω
Max. output level	+22 dBu

Phones Output

Type	¼" TRS mini jack
Max. output level	+7 dBu / 150 Ω

System Data (Noise)

Main mix @ -∞, channel fader @ -∞	-96 dBu / -101 dBu A-weighted
Main mix @ 0 dB, channel fader @ -∞	-82 dBu / -87 dBu A-weighted
Main mix @ 0 dB, channel fader @ 0 dB	-80 dBu / -85 dBu A-weighted

External USB Switching Power Supply

Mains voltage	100-240 V, ~ 50/60 Hz
Power consumption	0.9 W
Power connector	USB, type A

USB

Connector	Type B
Converter	16-bit
Sample Rate	48 kHz

Size/Weight

Dimensions (H x W x D)	1.8 x 4.5 x 5.4" 46 x 114 x 136 mm
Weight	0.83 lbs / 0.38 kg

Please note these specifications are preliminary and conceptual in nature, and as such are subject to change as product development progresses. This information is supplied for market research purposes only and is not to be made public in any manner. This document is solely the property of The MUSIC Group, or one of its subsidiaries, and must be surrendered upon request of the owner.

For service, support or more information contact the BEHRINGER location nearest you:

Europe
MUSIC Group Services UK
Tel: +44 156 273 2290
Email: CARE@music-group.com

USA/Canada
MUSIC Group Services NV Inc.
Tel: +1 702 800 8290
Email: CARE@music-group.com

Australia
MUSIC Group Services AU Pty Ltd
Tel: +61 03 9877 7170
Email: CARE@music-group.com

Japan
MUSIC Group Services JP K.K.
Tel: +81 3 6231 0454
Email: CARE@music-group.com

Technical specifications and appearances are subject to change without notice and accuracy is not guaranteed. BEHRINGER is part of the MUSIC Group (music-group.com). All trademarks are the property of their respective owners. MUSIC Group accepts no liability for any loss which may be suffered by any person who relies either wholly or in part upon any description, photograph or statement contained herein. Colors and specifications may vary from actual product. MUSIC Group products are sold through authorized fulfillers and resellers only. Fulfillers and resellers are not agents of MUSIC Group and have absolutely no authority to bind MUSIC Group by any express or implied undertaking or representation. This manual is copyrighted. No part of this manual may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording of any kind, for any purpose, without the express written permission of MUSIC Group IP Ltd. ALL RIGHTS RESERVED. © 2012 MUSIC Group IP Ltd. Trident Chambers, Wickhams Cay, P.O. Box 146, Road Town, Tortola, British Virgin Islands. 985-10000-00484