

BUGERA GUITAR AMPS

Model	Power Rating	Total Channels	Clean Channel	Crunch Channel	Lead Channel	Amplifier Valves Included	Optional Valve Operation	Preamp Valves	Onboard Reverb	3-Band EQ	Effects Loop	Line Output	Master Volume	Footswitch Included	Output Impedance	Speakers	Impedance	Dimensions (H x W x D)	Weight
BC30-212	30/15-Watts	2	✓	✓	✓	4 x EL84	5AR4/ 5U4 rectifier	4 x 12AX7, 1 x ECC83A	—	—	✓ (2)	—	✓	—	4, 8 or 16 Ohm	2 x 12" Models: 12G100B8 / 12G80A8	16 Ohm	20.4 x 27 x 10.8" 520 x 687 x 275mm	73.0 lbs 33.1 kg
V55	55-Watts	2	✓	—	✓	2 x 6L6	Triode/ Pentode	3 x 12AX7	✓	✓	✓	—	✓	FSB102A	4, 8 or 16 Ohm	1 x 12" Model: 12G70J8	8 Ohm	21.45 x 23.5 x 10.63" 545 x 597 x 270mm	50 lbs 22.5 kg
V55HD	55-Watts	2	✓	—	✓	2 x 6L6	Triode/ Pentode	3 x 12AX7	✓	✓	✓	—	✓	FSB102A	4, 8 or 16 Ohm	—	—	12.2 x 23.5 x 10.63" 310 x 597 x 270mm	37.5 lbs 17 kg
V22	22-Watts	2	✓	—	✓	2 x EL84	—	2 x 12AX7	✓	✓	✓	—	✓	FSB102A	4, 8 or 16 Ohm	1 x 12" Model: 12G70J8	8 Ohm	17.8 x 22.5 x 10.6" 453 x 572 x 270mm	42 lbs 19 kg
V5	5/1/0.1-Watts	1	—	—	—	1 x EL84	—	1 x 12AX7	✓	—	—	Phone	✓	—	4 Ohm	1 x 8" Model: 8G30A4	4 Ohm	14.1 x 14.1 x 8.62" 356 x 356 x 219mm	22 lbs 10 kg
BC15	15-Watts	2	✓	—	✓	—	—	1 x 12AX7	—	—	—	—	✓	—	4 Ohm	1 x 8" Model: 8G30A4	4 Ohm	13.125 x 14.06 x 6.38" 322 x 357 x 162mm	12.3 lbs 5.6 kg
TRIREC	1-100 Watts Variable	3	✓	✓	✓	4 x 6L6	EL34	5 x 12AX7	✓	✓	✓	✓	✓	✓	4, 8 or 16 Ohm	NA	NA	12.2 x 23.11 x 9.65" 310x587x245mm	52 lbs 23.6kg
MAGICIAN	1-85 Watts Variable	3	✓	✓	✓	4 x 6L6	EL34	4 x 12AX7	✓	✓	✓	✓	✓	✓	4 or 8 Ohm	TBA	8 Ohm	19.69x23.58x10.24" 500 x 599 x 260mm	62 lbs 28.2kg
1960	150-Watts	2	—	—	—	4 x EL34	—	3 x ECC83	—	✓	✓	—	—	—	4, 8 or 16 Ohm	—	—	9.8 x 27 x 9.7" 249 x 687.3 x 246mm	47 lbs 21.5 kg
1990	120-Watts	2	✓	—	✓	4 x 5881	—	3 x ECC83	✓	✓	✓	✓	—	FSB102	4, 8 or 16 Ohm	—	—	9.8 x 27 x 9.7" 249 x 687.3 x 246mm	47 lbs 21.5 kg
333	120-Watts	3	✓	✓	✓	4 x 6L6	EL34	4 x 12AX7	✓	✓	✓ (3)	with Level Control	✓	FSB104	4, 8 or 16 Ohm	—	—	9.8 x 27 x 9.7" 249 x 687.3 x 246 mm	47 lbs 21.5 kg
333-212	120-Watts	3	✓	✓	✓	4 x 6L6	EL34	4 x 12AX7	✓	✓	✓ (3)	with Level Control	✓	FSB104	4, 8 or 16 Ohm	2 x 12" Model: 12G70J8	16 Ohm	20.4 x 27 x 9.75" 518.5 x 687.3 x 247.6mm	63 lbs 28.5 kg
333XL	120-Watts	3	✓	✓	✓	4 x EL34	6L6	4 x 12AX7	✓	✓	✓ (3)	with Level Control	✓	FSB104	4, 8 or 16 Ohm	—	—	9.8 x 27 x 9.7" 249 x 687.3 x 246 mm	47 lbs 21.5 kg
333XL-212	120-Watts	3	✓	✓	✓	4 x EL34	6L6	4 x 12AX7	✓	✓	✓ (3)	with Level Control	✓	FSB104	4, 8 or 16 Ohm	2 x 12" Model: 12G70J8	16 Ohm	20.4 x 27 x 9.75" 518.5 x 687.3 x 247.6mm	63 lbs 28.5 kg
6260	120-Watts	2	✓	✓	✓	4 x 6L6	EL34	5 x 12AX7	✓	✓	✓	✓	—	FSB104A	4, 8 or 16 Ohm	—	—	9.8 x 27 x 9.7" 249 x 687.3 x 246 mm	47 lbs 21.5 kg
6260-212	120-Watts	2	✓	✓	✓	4 x 6L6	EL34	5 x 12AX7	✓	✓	✓	✓	—	FSB104A	4, 8 or 16 Ohm	2 x 12" Model: 12G70J8	16 Ohm	20.4 x 27 x 9.75" 518.5 x 687.3 x 247.6mm	63 lbs 28.5 kg
6262	120-Watts	2	✓	✓	✓	4 x 6L6	EL34	6 x 12AX7	✓	✓ (2)	✓	✓	—	FSB104A	4, 8 or 16 Ohm	—	—	9.8 x 27 x 9.7" 249 x 687.3 x 246mm	47 lbs 21.5 kg
6262-212	120-Watts	2	✓	✓	✓	4 x 6L6	EL34	6 x 12AX7	✓	✓ (2)	✓	✓	—	FSB104A	4, 8 or 16 Ohm	2 x 12" Model: 12G70J8	16 Ohm	20.4 x 27 x 9.75" 518.5 x 687.3 x 247.6mm	63 lbs 28.5 kg